

Ferramentas			Cabo de cobre	
HC35 / CHC35 / HC35CP / CHC46 + Adaptador		CH6 / CHC6-8 / CH6-H	mm ²	AWG / MCM
Matrizes				
Circunferencial	Hexagonal	Circunferencial		
M10	MH10	C10	5mm ² / 6mm ²	10 AWG
M8	MH8	C8	10 mm ²	8 AWG
M6	- - -	C6	13 mm ²	6 AWG
M5	MH5	C5	16 mm ²	5 AWG
M4	MH4	C4	25 mm ²	4 AWG
M3	- - -	- - -	27 mm ²	3 AWG
M2	MH2	C2	35 mm ²	2 AWG
M1	MH1	C1	40 mm ²	1 AWG
M25	MH25	C25	50 mm ²	1/0 AWG
M26	MH26	C26	70 mm ²	2/0 AWG
M27	MH27	C27	85 mm ²	3/0 AWG
M28	MH28	C28	95 mm ²	4/0 AWG
M29	MH29	C29	120 mm ²	250 MCM
M30	MH30	- - -	150 mm ²	300 MCM
M31	MH31	- - -	185 mm ²	350 MCM
M32	MH32	- - -	200 mm ²	400 MCM
M33	- - -	- - -	220 mm ²	450 MCM
M34	MH34	- - -	240 mm ²	500 MCM
M35	- - -	- - -	270 mm ²	550 MCM
M36	MH36	- - -	300 mm ²	600 MCM
M38*	- - -	- - -	350 mm ²	700 MCM
M40*	MH40*	- - -	400 mm ²	750 MCM
M44**	MH44**	- - -	500 mm ²	1000 MCM
- - -	- - -	- - -	- - -	- - -
- - -	- - -	- - -	- - -	- - -
- - -	- - -	- - -	- - -	- - -

* Somente Terminais.

** Somente Cabeçote Prensa CHC46 + Adaptador.

